

Network Administrator

Estimating, Repair, Shop Management
and Parts Catalogs User's Guide

ShopKey

Poway, California
2002

**Copyright © 2002 SnapOn Diagnostics and Mitchell Repair Information Company, LLC
All Rights Reserved**

DISCLAIMER OF WARRANTIES: Although the information contained within this volume has been obtained from sources generally believed to be reliable, no warranty (expressed or implied) can be made as to its accuracy or completeness, nor is any responsibility assumed by Mitchell Repair Information Company (MRIC) or anyone connected with it for loss or damages suffered through reliance on any information contained in this volume. SPECIFICALLY, NO WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR ANY OTHER WARRANTY IS MADE OR TO BE IMPLIED WITH RESPECT TO THIS VOLUME AND ITS CONTENTS. In no event will MRIC be liable for any damages direct or indirect, consequential or compensatory, including, without limitation, lost profits, for any representations, breaches or defaults arising out of the use of this volume. Customer agrees to indemnify MRIC and hold it harmless against all claims and damages, including without limitation, reasonable attorney's fees arising out of the use of this volume, unless such claims or damages result from the infringement of any copyright or other proprietary right of any third party. This document contains confidential and trade secret information of MRIC. Any unauthorized reproduction, photocopy, or use of the information herein, in whole or in part, without the prior written approval of MRIC is prohibited.

Mitchell Repair Information Company, LLC, Mitchell OnDemand5, ShopKey and MRIC are registered trademarks used under license herein.

Microsoft is a registered trademark of Microsoft Corporation.

Windows XP, Windows 2000 and NT are registered trademark of Microsoft Corporation.

Windows is a registered trademark of Microsoft Corporation.

3Com is a registered trademark of 3Com Corporation.

lomega Zip is a registered trademark of lomega Corporation.

Other trademarks and registered trademarks used in this document are the property of their owners.

● Contents

● INTRODUCTION	1
Welcome	1
About this Network Guide	1
Support Resources.....	1
● TWO TO THREE USER CONFIGURATION	2
The Two to Three User System.....	2
Details - Two to Three User Network	2
● FOUR OR MORE USER CONFIGURATION	4
Server Based Systems Supporting Four to Five Users	4
● WINDOWS XP AND 2000 NETWORK CONFIGURATION	6
Network Configuration.....	6
General XP Configuration.....	6
XP Resource Naming Conventions	11
The Server when Viewed from Workstations	11
Make sure these shares are available before installing the software.	11
Windows XP TCP/IP Settings.....	12
Windows 2000 TCP/IP Settings.....	12
Enabling NetBIOS over TCP/IP on Windows 2000.....	14
Windows 2000 Naming.....	15
Windows 2000 Resource Naming and Sharing Conventions.....	15
Windows 2000 Workgroup Naming	16
● WINDOWS 98 SECOND EDITION NETWORK CONFIGURATION	17
Windows 98 SE Network Configuration.....	17
Windows 98 SE General Configuration	17
Naming Conventions.....	18
The Server when Viewed from Workstations	19
Make sure these shares are available before installing the software.Windows 98 SE TCP/IP	
Settings	19
Windows 98 SE TCP/IP Settings	20
Windows 98 SE Workstation TCP/IP Settings.....	20
● WORKSTATION MAPPING	21
Drive Letter Assignments (Mapping).....	21
● INSTALLATION	22
Application Installation	22
● USING WINDOWS 2000 SERVER	24
Windows 2000 Server	24
Summary	24

Welcome



ShopKey customers find that a network solution increases shop productivity and profits. Repair and Estimating information can be accessed from multiple PCs simultaneously and shop management orders can be viewed and updated by multiple users updating a single, common database.

This Network Guide details the architecture and general hardware recommendations for a network serving as a platform for estimating, repair; shop management and parts catalog multi-user software. Although Estimating, Repair, Cataloging and Shop Management will operate on a large range of platforms, the specified architecture offers reliability and ease of support. Deviating from these specified settings and conventions could result in system configurations that are more difficult and time consuming to support.

Hardware and software recommendations made within this document have been thoroughly tested. Dell, HP, IBM or Compaq business grade computers should be specified. Windows XP™ is the preferred operating system for ease of support; ShopKey is however fully supported on, Windows 2000, Windows ME, and Windows 98 Second Edition

About this Network Guide

This guide answers questions that may arise when designing a network that is efficient and easy to support. It is designed for use by a qualified network professional as a supplement to other documentation provided with ShopKey software.

In addition to providing all of the information needed to successfully configure a network, this guide also includes:

- Hardware recommendations.
- Wiring specifications.
- Naming conventions.
- General Installation instructions.

This Network Guide is provided to bridge the gap between the Standard documentation and the added complexity of multi-user systems.

Support Resources



While setting up ShopKey products in a multi-user environment is not especially difficult for persons with previous networking experience, it is highly recommended that you acquire the assistance of a Microsoft Certified Professional or other trained networking professional. This document assumes a basic knowledge of networking and ShopKey *cannot* provide technical support on networking functions external to the ShopKey software.

In addition to this Network Administrators guide, setup and other networking information is available in the documentation that came with your ShopKey product.

If you don't find what you need in any of these resources, technical support is available at (800) 944-3877: Monday-Friday 6:30 am to 4:30 pm Pacific Time.

• Two to Three User Configuration


The Two to Three User System



Typical Peer-to-Peer Star Network

Installing a network requires multiple computers. Each computer on the network has a specific role. Those roles can be workstation, server, or workstation/server. When a computer is configured as both a workstation and a server, that computer is configured to share its both DVD-Rom drives, Iomega Zip Drive, Printer(s) and hard disk space. This type of configuration is best suited for a two to three user network. Use 3Com or Intel 100 Megabit Network Adapters, a 3Com 100 Megabit Hub or Switch and Category 5 UTP cable or a 100 Megabit Router/Switch. (Note: A Router/Switch will allow all the computers in your shop to share a broadband internet connection permitting easy connection to SkopKey Rewards Site.

Systems designed for more than four users will be discussed later in this document. Networks supporting a shop management application must also be equipped with a backup power supply and an Iomega™ Zip drive.



Workgroup Name: [SHOP NAME]
 Workstation/Server Name: SERVER
 Workstation Names: WKS1, WKS2, etc.

Details - Two to Three User Network

ShopKey recommends that each user on the 2-3-user network use Windows XP Pro as the operating system. You must use 3Com or Intel network adapters. Each system is configured according to the table below.

<p>Workstation/Server</p> <ul style="list-style-type: none"> • Business Grade 500Mhz or better -Win XP Pro or 2000 • 17 inch Monitor, 256 MB Ram or better • 3Com or Intel Ethernet Adapter • HP DeskJet 800/900 Series DeskJet or HP LaserJet Printer • 20 GB or better Hard Drive (C:) • Iomega Zip Drive (D:) • DVD-ROM Drive (E:) • DVD-ROM Drive (F:) 	<ul style="list-style-type: none"> • Create a directory on C: drive called "APPS", share this directory giving everyone full control, the share name should be set to: "SRV-APPS". • Share the CD-ROM - Read-Only, set the share name to: "SRV-CDROM". • Share the DVD-Rom Drives as Read-Only, set the share name to: "SRV-DVDROM1 and SRV-DVDROM2" • Share the Iomega-Zip Drive to everyone with Full control as "SRV-IOMEGA"(See Backup information in the Management Manual.) • Share printer as "SRV-[Printer Name]"
---	--

<p>Workstations</p> <ul style="list-style-type: none"> • Business Grade 233Mhz or better -Win XP or 2000 • 17 inch Monitor, 128 MB Ram or better • 3Com or Intel Ethernet Adapter • 8 GB Hard Drive (C:) • DVD-ROM Drive (D:) 	<ul style="list-style-type: none"> • Map \\SERVER/SRV-APPS to M: • Map \\SERVER/SRV-CDROM to N: • Map \\SERVER/SRV-DVDROM1 to P: • Map \\SERVER/SRV-DVDROM2 to Q: • Map \\SERVER/SRV-IOMEGA to R: • Install network printer \\SERVER\RV-[Printer Name]
---	--

ShopKey Reps and Technical Support have found that Mapping the drives can be a troublesome for some users the mapping is lost. We recommend creating a batch file called drives.bat and using the NET USE command to map the drives and placing this file under the C: drive of each work station. Placing a shortcut to the batch file in each computers StartUp folder (set it to run minimized and exit close on exit) will ensure each computer will never loose drive mappings. Below is an example of drive.bat for the above scenario above:

Rem drive.bat batch file


```
NET USE M: \\SERVER/SRV-APPS
NET USE N: \\SERVER/SRV-CDROM
NET USE P: \\SERVER/SRV-DVDROM1
NET USE Q: \\SERVER/SRV-DVDROM2
NET USE R: \\SERVER/SRV-IOMEGA
EXIT
```

• Four or More User Configuration

Server Based Systems Supporting Four to Five Users

A server-based network maintains the “server” as the manager of the network. In this way, the server can house and administer software, file sharing, file saving, allocation of printers and other communication connections. This configuration is ideal for four to fifteen users. Use 3Com or Intel 100 Megabit Network Adapters, a 3Com 100 Megabit Hub, Switch or Router/Switch and Category 5 UTP cable.

Server-based networks offer high reliability and scalability. The server in this model uses Windows 2000 or XP Pro as the operating system. Note: Windows 2000 and Windows XP Pro are excellent choices for the operating system for a network of four to five users. Larger systems should use Windows 2000 Server. Refer to the section on Windows NT beginning on 24. The server is not used as a workstation. Servers supporting a shop management application must be equipped with a backup power supply and an Iomega™ Zip drive.



Workgroup Name:
Server Name:
Workstation Names:

[SHOP NAME]
SERVER
WKS1, WKS2, WKS3, WKS4, etc.

Details - Four to Five User Network

Note: ShopKey Repair and Estimating for up to ten users typically does not require a dedicated server. When Shop Management is included in a system with four or more users, a server should be used.

Each computer in the server-based network should use Windows XP Pro or Windows 2000 Professional as the operating system. Each system is configured according to the table below

<p>Server</p> <ul style="list-style-type: none"> • Business Grade 500Mhz or better –XP or 2000 • 15 inch Monitor, 256 MB Ram or better • 3Com or Intel Ethernet Adapter • HP DeskJet 800/900 Series DeskJet or • HP LaserJet Printer • 20 GB or better Hard Drive (C:) • Iomega Zip Drive (D:) • DVD-ROM Drive (E:) • DVD-ROM Drive (F:) 	<ul style="list-style-type: none"> • Create a directory on C: drive called “APPS”, share this directory giving everyone full control, the share name should be set to: “SRV-APPS”. • Share the CD-ROM - Read-Only, set the share name to: “SRV-CDROM”. • Share the DVD-Rom Drives as Read-Only, set the share name to: “SRV-DVDROM1 and SRV-DVDROM2” • Share the Iomega-Zip Drive to everyone with Full control as “SRV-IOMEGA”(See Backup information in the Management Manual.)” • Share printer as “SRV-[Printer Name]”
--	---

Workstations

- Business Grade 233Mhz or better –Win XP or 2000
- 17 inch Monitor, 128 MB Ram or better
- 3Com or Intel Ethernet Adapter
- 8 GB Hard Drive (C:)
- DVD-ROM Drive (D:)

- Map \\SERVER/SRV-APPS to M:
- Map \\SERVER/SRV-CDROM to N:
- Map \\SERVER/SRV-DVDROM1 to P:
- Map \\SERVER/SRV-DVDROM2 to Q:
- Map \\SERVER/SRV-IOMEGA to R:
- Install network printer \\SERVER/SRV-[Printer Name]

• Windows XP and 2000 Network Configuration


Network Configuration

Regardless of which operating system you choose for your shop, each computer in the system is assigned specific parameters. Those parameters include the Workgroup-name, host (or workstation) name, IP address, Subnet Mask, connection method, and specific drive letter mappings. Observing these conventions will provide optimal performance and ease of support. Workstations in the network should not have their resources shared unless necessary.

General XP Configuration


Whether the server acts as a dedicated server or a server/workstation, configuration is the same. Configure the network to use TCP/IP as the default protocol; you must also enable NetBIOS over TCP/IP in Windows in all Operating systems. On XP systems, from the Windows Desktop, find My Network Places. Right click on that Icon and choose properties.

This will bring up the Network connections folder. In Windows XP, the Network Connections dialog box includes both Dialup (modem) connections and Network card connections.





Find the Icon in the Folder that is your Network card connection to the local LAN. In the graphic to the left, it is the Local Area Connection and that is what it should be called on other Windows XP computers. You may have other connections listed.

LAN or High-Speed Internet




Right Click on the Local Area Connection icon and choose Properties from the Popup menu.

This will bring up the Local Area Connection Properties dialog box illustrated to the right. File and Print Sharing and other protocols must be installed. TCP/IP and NetBIOS support must be installed. If you do not see NWLink NetBIOS listed under “This Connection uses the following items:” list, you must install it by clicking on the Install button.



When you click on the Install button, you will get this dialog box. Next, click on Protocol and click the Add button.



When you click on the Add button, you will get the following dialog box. Click on the NWLink IPX/SPX/NetBIOS Compatible Transport Protocol and click the OK button. In Windows XP the NetBIOS protocol cannot be installed without the IPX/SPX protocol which is used on Novell Networks. This can be confusing. NWLink is a Windows XP's combination Network Protocol for NetBIOS and IPX/SPX so don't be concerned



This will take you back to the Local Area Connection Properties Dialog box. Here will notice that 2 protocols were added since one cannot be installed without the other; NWLink NetBIOS and NWLink IPX/SPX/NetBIOS Compatible Transport Protocol.


Use the scroll to the right of the install protocols to find TCP/IP. Double click on Internet Protocol (TCP/IP) in the list.

T




will bring up the Internet Protocol dialog box as illustrated below.


Click on the Advanced button in this dialog box.




Click on the WINS tab in this dialog box.



The WINS property sheet will display. Click on the “Enable NetBIOS over TCP/IP” Radio Button and click OK. Close the rest of the boxes, you are done.








XP Naming - Using strict naming conventions allows any network administrator or technical support person to easily identify all the components and roles within your network. Although assigning vanity names to the server and workstations may be appealing, we recommend that you use the standardized naming conventions we recommend. Non-standard name can be very difficult and time consuming for administrators and tech support personnel.

We recommend naming the server simply as *SERVER* and workstations as *WKS1*, *WKS2*, *WKS3* and so on and other resources as described in the following section.


Note: Each computer on the network *must* have the same Workgroup name. If you must change the workgroup on XP, click on the Network ID button and follow the instructions.

To change the name of the computer, right mouse click on 'My Computer' found on the Windows XP Desktop. Select Properties and click on Change. Name the server 'Server'.



Click OK. Click OK again to restart the computer.

XP Resource Naming Conventions



Naming the resources attached to a server or workstation with plain English names makes sense. Doing so allows the system to be easily diagnosed in the event there is a problem. To establish the naming scheme first create a directory on the server C : drive called “APPS”. This directory will be shared to all users with **Full Control** with the Share Name of “SRV-APPS”. Share the first DVD-ROM with the Share Name set to “SRV-DVDROM1.

Allow network users to change my files

Remove the checkmark from “Allow network users to change my files”. This saves on resources.

Share the second DVD-ROM with the Share Name set to “SRV-DVDROM2 . Apply the same setting as the first drive.

Share the Iomega Zip Drive with the Share Name set to “SRV-IOMEGA and set the Access Type to Full. Printers should also be shared with plain English names that include the name of the computer. In this example, we have shared a DeskJet 890 on the Server as “SRV-DJ890”

The Server when Viewed from Workstations

Viewing the SERVER from Network Neighborhood will now list the following resources:


- SRV-APPS
- SRV-CDROM
- SRV-DVDROM1
- SRV-DVDROM2
- SRV-IOMEGA
- SRV-[PRINTER_NAME]

Make sure these shares are available before installing the software.

Windows XP TCP/IP Settings

Each computer in the network has a unique IP address and the same Subnet Mask. Windows XP and Windows 2000 unless otherwise required do not require setting TCP/IP address. The operating system will automatically assign unique IP address to each computer. If the system is equipped with a Router/Switch, enable DHCP to assign IP address's to each workstation.

The **XP Server/Workstation** or **Server** should have the following protocols displayed when viewing the “The Local Area Connection Properties”.



Windows 2000 TCP/IP Settings




Local Area Connection



Just as Windows XP, whether the Windows 2000 computer acts as a dedicated server or a server/workstation, the requirement are the same.

Configure the network to use TCP/IP as the default protocol and enable NetBIOS over TCP/IP. On Windows 2000 systems, from the Windows 2000 Desktop, find My Network Places. Right click on that Icon and choose properties. When the property page displays click on “Local Area Connection”.



When the “Local Area Connection Status” windows opens click on Properties.



Click on the Install button when the “Local Area Connections” window opens.




Click on the Add button, select “NetBEUI Protocol” and click OK.




When the Property sheet appears, double click on “Internet Protocol (TCP/IP)”.

Enabling NetBIOS over TCP/IP on Windows 2000

With the “Internet Protocol (TCP/IP) Properties” page open, click on the Advanced button.




Click on the “WINS” tab, The WINS property sheet will display. Click on the “Enable NetBIOS over TCP/IP” Radio Button and click OK. Close the rest of the boxes, you are done.



Windows 2000 Naming

Naming should follow the same conventions as detailed for Windows XP. Uniform naming allows administrators or technical support personnel to easily identify all the components and roles within your network. **We recommend naming the server simply as *SERVER* and workstations as *WKS1*, *WKS2*, *WKS3* and so on and other resources as described in the following section.**

Windows 2000 Resource Naming and Sharing Conventions




Naming the resources attached to a Windows 2000 server or workstation with plain English names makes sense. Doing so allows the system to be easily diagnosed in the event there is a problem. To establish the naming scheme first create a directory on the server C : drive called "*APPS*". This directory will be shared to all users with **Full Control** with the Share Name of "*SRV-Apps*". Click on the Permissions button to verify that "*Everyone*" has full control.. Share the first DVD-ROM with the Share Name set to "*SRV-DVDROM1*. DVD-

ROM drive permissions should be set to allow only Read rights to conserve resources.


Share the second DVD-ROM with the Share Name set to "*SRV-DVDROM2* . Apply the same setting as the first drive.

Share the Iomega Zip Drive with the Share Name set to "*SRV-IOMEGA* and set the Permissions to Full Control, Change and Read.. Printers should also be shared with plain English names that include the name of the computer. In our example, we have shared a DeskJet 890 on the Server as "*SRV-DJ890*"




Windows 2000 Workgroup Naming

As discussed earlier, all computers on the network *must* belong to the same Workgroup. To change the workgroup name on Windows 2000 you must first right mouse click on 'My Computer' from the Windows desktop and click on "Properties".




If you change the Computer Name or Workgroup name, you must reboot the computer when completed.



On the System Properties page click on the "Properties" button.

This will allow you to change the workgroup name.



• Windows 98 Second Edition Network Configuration


Windows 98 SE Network Configuration

Regardless of which operating system you choose for your shop, each computer system parameters are similar. Those parameters include the Workgroup-name, host (or workstation) name, IP address, Subnet Mask, connection method, and specific drive letter mappings. Observing these conventions will provide optimal performance and ease of support. Workstations in the network should not have their resources shared unless necessary. If every computer on the network is Windows 98 Second Edition, you will have to assign IP address's to each machine. **We do not recommend using Windows 98 SE as workstations connected to a Windows XP or Windows 2000 computer.**


Windows 98 SE General Configuration

Whether the server acts as a dedicated server or a server/workstation, configuration is the same. Configure the network to use TCP/IP as the default protocol. **NetBEUI must also be installed.** IPX/SPX protocol is unnecessary and may be removed if installed.

To install NetBEUI protocol, right mouse click on “Network Neighborhood” from the Windows 98 desktop. Click on “Properties” to reveal the Network configuration sheet. Click on the “Add” button




Double click on “Protocol”,




click on “Microsoft” under Manufacture, use the scroll bar on the right to find “NetBEUI”. Double Click on it. Click OK, and reboot the computer when prompted. NetBIOS over TCP/IP will automatically be enabled.

Client for Microsoft Networks installed. The Client for Microsoft Networks Properties should be configured to **Quick Logon**. This prevents users from losing mapped network connections in the event a workstation is started without the server running.



Identification Settings




Quick Logon Option

Naming - Using strict naming conventions allows any network administrator or technical support person to easily identify all the components and roles within your network. Although assigning vanity names to the server and workstations may be appealing, we recommend that you use the standardized naming conventions we recommend. Non-standard name can be very difficult and time consuming for administrators and tech support personnel.

We recommend naming the server simply as **SERVER** and workstations as **WKS1**, **WKS2**, **WKS3** and so on and other resources as described in the following section.

Naming Conventions

Naming the resources attached to a server or workstation with plain English names makes sense. Doing so allows the system to be easily diagnosed in the event there is a problem. To establish the naming scheme first create a directory on the server C : drive called "APPS". This directory will be shared to all users with **Full Control** with the Share Name of "SRV-APPS".




Apps Folder Shared

Share the CD-ROM with the Share Name set to “SRV-CDROM and set the Access Type to Read-Only.

Share the first DVD-Rom with the Share Name set to “SRV-DVDROM1 and set the Access Type to Read-Only. Share the second DVD-Rom drive with the Share Name set to “SRV-DVDROM2 and access type of Read Only.

Share the Iomega Zip Drive with the Share Name set to “SRV-IOMEGA and set the Access Type to Full.

Printers should also be shared with plain English names that include the name of the computer. In this example, we have shared a DeskJet 890 on the Server as “SRV-DJ890”



Sharing DeskJet 890

The Server when Viewed from Workstations

Viewing the SERVER from Network Neighborhood will now list the following resources:

- SRV-APPS
- SRV-CDROM
- SRV-DVDROM1
- SRV-DVDROM2
- SRV-IOMEGA
- SRV-[PRINTER_NAME]

Make sure these shares are available before installing the software.

Windows 98 SE TCP/IP Settings




3Com NIC
IP: 192.168.0.1
Subnet: 255.255.255.0

Each computer in the Windows 98 network has a unique IP address and the same Subnet Mask. We recommend using TCP/IP settings reserved by the Internet Address and Numbering Authority (IANA). The 192.168.0.0 range is one of the standards reserved for private networks (RFC1918). The settings defined in our standard is as follows:

IP Address	Subnet Mask	Address Range
192.168.0.0	255.255.255.0	192.168.0.1-192.168.255.254

Using this addressing scheme, the **Server/Workstation** or **Server** should have the following TCP/IP network properties: File and Print Sharing should also be enabled.



File and Print Sharing Enabled

Windows 98 SE Workstation TCP/IP Settings

Workstations must be configured with a similar IP addressing scheme. If resources attached to a workstation are to be shared, make certain the share name is preceded by the workstation name. For example, a printer attached to WKS1 might be named "WKS1-HP890".

• Workstation Mapping

Drive Letter Assignments (Mapping)



Workstation



3Com NIC

IP: 192.168.0.3

Subnet: 255.255.255.0

Each workstation requires drive mappings to resources shared by the server. There are five resources required for most configurations:

- APPS directory on the server.
- SRV-CDROM drive on server.
- DVD-ROM1 drive on the server.
- DVD-ROM2 drive on the server.
- IOMEGA Zip on the server.
- Printer attached to the server.

Use the same drive mappings for each workstation on the network. Establish these mappings before installing any software. Resource mapping is detailed in the following table:

Drive Letter	Resource
M:	SERVER/SRV-APPS
N:	SERVER/SRV-CDROM
P:	SERVER/SRV-DVDROM2
Q:	SERVER/SRV-DVDROM2
R:	SERVER/SRV-IOMEGA
PRINTER	SERVER/SRV- [PRINTER_NAME]


Once each workstation is configured, applications are found on M : , Estimating on N ; , Repair Data DVD Rom 1 on P : and Repair Data DVD-Rom 2 on Q : and a network or local printer is installed. R : is assigned to the Iomega Zip drive which is used to store back-up copies of the shop management database. Note: Estimating data is automatically copied to the servers hard drive – see the OnDemand5 User Guide for more information.

ShopKey Reps and Technical support have found that Mapping the drives can be a troublesome for some users the mapping is lost. We recommend creating a batch file called drives.bat and using the NET USE command to map the drives and placing this file under the C: drive of each work station. Placing a shortcut to the batch file in each computers StartUp folder (set it to run minimized and exit close on exit) will ensure each computer will never loose drive mappings. Below is an example of drive.bat for the above scenario above:

Rem drive.bat batch file

```
NET USE M: \\SERVER/SRV-APPS
NET USE N: \\SERVER/SRV-CDROM
NET USE P: \\SERVER/SRV-DVDROM1
NET USE Q: \\SERVER/SRV-DVDROM2
NET USE R: \\SERVER/SRV-IOMEGA
EXIT
```

Application Installation



The installation process for all Multi-User Repair, Estimating and Shop-Management, and Parts Catalog software is a three-step process.

- Administrative Installation.
- Application Installation.
- Application Configuration.



Repair and Estimating information is delivered to the client from within the same application; Shop Management software is a separate application. The Administrative Installation for both applications should be performed at a workstation, **pushing** the files to the server on the M: drive in the appropriate subdirectory. The subdirectory is referred to as the *Administrative Program Path*.

Administrative Installation

Use the following paths for each application when performing the Administrative Installation when pushed from a workstation: (Drives P:, Q:, & R: are used during Application Configuration.)

Program	Administrative Program Path
ShopKey	M:\SHOPKEY \Repair
Management Software	M:\SHOPKEY \Manager
Parts Catalog (I.e.: ShopCat)	M:\LaserCat2000
Parts Catalog Data(I.e. ShopCat)	M:\data
Part & Labor Guide CD	Copied to Hard Drive
Repair Estimating	N:
Repair DVD #1	P:
Repair DVD #2	Q:
Iomega Zip Drive	R:

During the Administrative Installation the setup program will default to the C: \ drive. Change the default drive letter to M:, making sure to preserve the path. When the Administrative Installation is complete, please put the Installation CD's away in a safe place. Data CD's and DVD's should be registered according to the application user guides.

Workstation Application Installation

Each workstation requires installation of the client application. Please consult the user guide for each application.

Management Software Configuration Consideration

Management application configurations can be found in the *Getting Started* booklet. Probably the most important configuration to be considered is the backup parameter. The database created and used by the management software will be an extremely valuable asset to your business – it **must be backed up**. The backup path found in Shop Data Setup should be set to R : , this is the drive associated with the Iomega Zip Drive.

Note: Although other backup solutions may be considered, backing up to an Iomega Zip drive is fully supported by ShopKey, This permits the database backup to be taken off site. Using this method backs the database up in seconds. We recommend using an Iomega 250 Megabyte Zip Drive.

Shop Data Setup window showing configuration options. The 'Default Settings' tab is active. Key settings include:

- Area Code: 619
- Promised Time: 5:30 PM
- Labor Technician: Please . Select
- Parts Technician: Please . Select
- Service Writer: Dwulet, John
- Income Account: Visa
- Use Phone # Mask:
- Phone # Mask: ###-###-#### (* = Any, # = Number)
- Bal. Due Warning on new order: # days past due: []
- Warn on Program Exit:
- Enable FaxMan Fax printer:
- Include Spouse on Invoice:
- Include Tax in Estimates:
- Include Recommendations on RO:
- Perform backups on:
 - Program Startup:
 - Program Exit:
 - End of Day:
- Location: R:

Series I/II Shop Data Setup

To configure automatic backup to the Iomega ZIP drive, put a checkmark in the box to perform backups at **Program Exit** and set the **Location** to R : .

Note: Please consult the management software Users Guide more information about this setting. The backup setting in management software is specific to each workstation, as such we recommend maintaining copied on at least one workstation as well as the Iomega Zip Drive.

• Using Windows 2000 Server

Windows 2000 Server



Windows 2000 Server can successfully be used as a server for Estimating, Repair, Shop Management and Parts Catalog software. A qualified Microsoft Certified Professional should be retained for installation and administration.

Implementing a network based on a Windows 2000 server should include the same drive mappings as detailed previously. Under no circumstances should the Administrative Installation ever be performed at the Server Console.

Server Configuration

Create an “APPS” directory on a volume. Share the folder as SRV-APPS and give everyone Full Control.

Administrative Installation

Never run the Administrative Installation at the NT Server console. Log into the server from a workstation, map drive M: to \\SERVER\SRV-APPS and push the install to the appropriate *Administrative Program Path*. For these applications,.

Preferably, Windows 2000 Server should not be used as a workstation. The Windows 2000 Server platform must be on Microsoft’s Hardware Compatibility List.

Note: Installing to a Windows 2000 Server other than in the prescribed method will result in poor performance.

Summary

This Network Guide provided instructions on setting up a network to support Estimating, Repair, Shop Management and Parts Catalog programs. Please have a qualified Microsoft Certified Professional (MCP) follow this guide for trouble free installations.